

The HE-302 Socket is a expansion unit for the HomeEasy range of products and is designed to work with all HomeEasy

products.

nsion unit for ducts and is omeEasy

Learn:

Product Operation:

Pairing/Deleting with Remote Control:

Up to Six remote control units can be paired with each Receiver Socket or Module. To program a socket insert the unit into a plug socket and switch on the power, now press the "Learn" button. The LED will start to flash, now press the selected "On" button on the remote control, the LED will stop flashing. The units are now paired together, you can test this by pressing the selected "On/Off" button.

Always refer to the original instructions when using with additional products.

Deleting Remote Control:

To delete a remote control that has been paired with a HE-302 receiver socket, simply press the "Learn" button. The LED will start to blink; press the "Off" button on the remote control, the LED will blink twice to confirm that the remote control has been removed from the receiver sockets memory.

Remote Socket reset:

To delete all the remote control units from the memory of the receiver socket, hold the "Learn" button for more than 6 seconds, the LED will start to blink continuously. Press a the "Learn" button again, the LED will blink twice to confirm that all paired remote controls have been deleted from the receiver sockets memory.

Product Specification:

Remote Control: HE-302 Input: 230V ~50Hz

Range: 30 Metres (Open Distance)

Frequency: 433.92MHz Max Load: 3000W (Resistive)

Indoor Use Only

Warning: *Never Exceed the Product Specification*

Contact: Helpline: 0845 2301 231

C H Byron 34, Sherwood Rd Aston Fields Bromsgrove B60 3DR

Tel: 0845 2301231 Fax: 01527 557701 Web: www.chbyron.com

E-mail:

support@chbyron.com









